

Versa-portion®

Compact Scale

Specifications

Display:

LED, 6 digits

Capacity:

Pound	Gram	Ounce
6.0 lb x 0.002 lb	3000 g x 1 g	60.0 oz x 0.02 oz
15.0 lb x 0.005 lb	6000 x 2 g	150.0 oz x 0.05 oz
30.0 lb x 0.01 lb	15000 g x 5 g	300.0 oz x 0.1 oz
60.0 lb x 0.02 lb	30000 g x 10 g	600.0 oz x 0.2 oz

Display Indicators:

Ounces, grams, pounds, net, center of zero, battery usage

Keyboard:

Rezero, Tare, On/Off, Unit

Resolution:

Display resolution 1/3,000
Internal resolution 1/90,000

Operating Humidity:

15 ~ 85% RH

Operating Temperature:

14°F to 104°F (-10°C to +40°C)

Power Consumption:

18 W when using DC power, 3 W when using rechargeable battery
(battery life: 60 hours of continuous usage)

Power Source:

AC 117/100 V, 240/230/220 V
DC 12 V/1.5A, DC 6 V 5Ah optional rechargeable battery

Calibration:

RLP-S: Grams

Dimensions:

Overall:
(W x D x H): 9.9 x 11.4 x 5.3 in (251.6 x 289.7 x 134.6 mm)

Package Size:

(W x D x H): 14.8 x 13.3 x 9.6 in (377 x 337 x 245 mm)

Platter Size:

9.3 x 7.8 in (237.2 x 198.0 mm)

Approximate Weight:

13.9 lb (6.3 kg)

Warranty:

One-year limited warranty

Approvals:

NTEP CC 10-068, Class III 3,000 d
Measurement Canada AM-5794, Class III 3,000d



APPROVALS



Measurement
Canada
Approved

Standard Features

- Compact design and easy to use
- Water and dust resistant and IP68
- Stainless steel housing with an ABS plastic base
- Removable weigh pan—quick and easy cleaning
- LED display
- AC adapter included
- Legal for Trade
- Meets HACCP requirements

Optional Features:

- Rechargeable battery

Part Number/Price

PART #	DESCRIPTION	CAPACITY	EST. SHIP WEIGHT	PRICE
115125	RLP-6S	6.00 x 0.002 lb	15 lb (6.3 kg)	Consult
115128	RLP-15S	15.00 x 0.005 lb	15 lb (6.3 kg)	Consult
115129	RLP-30S	30.00 x 0.01 lb	15 lb (6.3 kg)	Consult
115130	RLP-60S	60.00 x 0.02 lb	15 lb (6.3 kg)	Consult

Options/Accessories

PART #	DESCRIPTION	PRICE
108516	Rechargeable battery	Consult
108518	AC adapter 110-230 VAC, U.S. plug	Consult
129953	AC adapter, 110-230 VAC, Euro plug	Consult
115519	Additional operator guide	Consult